

## Kit # 261 Installation Instructions

This monitor repair kit is designed for the Wells-Gardner D9400 digital color monitors. Be sure to check that all the parts are included in the kit:

14 1 uF @ 50V	1 470 uF @ 25V
2 2.2 uF @ 50V	1 470 uF @ 50V
5 4.7 uF @ 50V	1 1000 uF @ 35V
1 4.7 uF @ 50V NP	4 2200 uF @ 25V
5 10 uF @ 50V or 63V	3 1 uF @ 250V
1 22 uF @ 25V	1 4.7 uF @ 400V
4 22 uF @ 50V	1 10 uF @ 250V
12 47 uF @ 25V	1 22 uF @ 250V
2 100 uF @ 16V or 25V	1 100 uF @ 160V
1 220 uF @ 25V	2 100 uF @ 250V
1 470 uF @ 16V or 25V	

Each capacitor is polarized and can only be inserted in one direction. Watch the polarity markings on each capacitor. Be sure the game is unplugged and install the following parts.

### Neck Board

C801 1 uF @ 50V	C827 1 uF @ 250V
C807 1 uF @ 250V	C836 47 uF @ 25V
C811 1 uF @ 50V	C839 47 uF @ 25V
C817 1 uF @ 250V	C841 22 uF @ 25V
C821 1 uF @ 50V	C946 47 uF @ 25V

### Power Supply

C513 220 uF @ 25V	C536 2200 uF @ 25V
C515 4.7 uF @ 400V	C537 2200 uF @ 25V
C520 1 uF @ 50V	C538 470 uF @ 25V
C532 100 uF @ 250V	C547 470 uF @ 16V or 25V
C534 100 uF @ 160V	C548 470 uF @ 25V
C535 2200 uF @ 25V	C580 10 uF @ 50V or 63V

## Main Board

C200	2.2 uF @ 50V	C605	22 uF @ 50V
C201	4.7 uF @ 50V	C702	4.7 uF @ 50V
C212	47 uF @ 25V	C703	47 uF @ 25V
C214	47 uF @ 25V	C707	1 uF @ 50V
C216	47 uF @ 25V	C708	1 uF @ 50V
C224	100 uF @ 250V	C710	1 uF @ 50V
C225	1 uF @ 50V	C711	1 uF @ 50V
C226	22 uF @ 50V	C712	1 uF @ 50V
C231	10 uF @ 50V or 63V	C721	1 uF @ 50V
C232	100 uF @ 16V or 25V	C901	22 uF @ 250V
C235	47 uF @ 25V	C908	22 uF @ 50V
C256	47 uF @ 25V	C909	1 uF @ 50V
C257	47 uF @ 25V	C920	47 uF @ 25V
C260	4.7 uF @ 50V NP	C925	10 uF @ 250V
C303	10 uF @ 50V or 63V	C926	47 uF @ 25V
C311	2200 uF @ 25V	C927	10 uF @ 50V or 63V
C312	1000 uF @ 35V	C955	10 uF @ 50V or 63V
C314	1 uF @ 50V	C956	4.7 uF @ 50V
C322	4.7 uF @ 50V	C957	100 uF @ 16V or 25V
C603	1 uF @ 50V	C958	22 uF @ 50V