

Comparison of Happ Credit Accumulator/Timer, 42-1138-00, and Accumulating Vending Timer 42-6976-00

	Power Supply	Activates by Switch	No. of Coins Counted	Timer Length	Timer Adjustment	Dual Pricing Option	Manual "Push to Vend" Option and can power an illuminated button	"Time Adding" Example: "5 Minutes for \$1.00, 10 minutes for \$2.00"	Output
42-1138-00	120 VAC or 12-17 VDC	Yes	1 to 16	.2 seconds (no delay) to 10 minutes	On-Board Trim Pot, continuously variable	Yes, can give a second vend for a different price, if desired.	Yes, Can be set to light a "Push to Vend" button. Timer will start when button is pushed. Can be set as below, also.	No, adding coins during timing cycle does not increase time	DPDT Relay
42-6976-00	12 VDC	Yes	1 to 7	15 Seconds to 31 Minutes	Dip Switch in 15 Second Increments	No, single price only.	No, timer starts as soon as the proper amount of coins are dropped.	Yes, adding coins during timing cycle adds another time increment to the total time	SPDT Relay

Happ Web Page for 42-1138-00 <http://www.happcontrols.com/amusement/acesor/42113810.htm>

Happ Web Page for 42-6976-00 <http://www.happcontrols.com/amusement/acesor/42697600.htm>