

CELEBRATION VIDEO TOPPER

This innovative topper design creates a new level of excitement on your casino floor and stimulates additional game play. Topper interfaces into the SAS line to detect a hand pay signal from the slot machine and when the selected level of hand pay is achieved the topper triggers a "Celebration Event."

- **Celebration Event options include ANY or ALL of:**
 - Confetti launcher throws out bursts of confetti
 - Loud 8 Watt Stereo audio celebration alarm/sounds through two 2" x 4" speakers
 - Standard or customizable videos on the LCD
 - Flashing multi-color RGB LED's on both sides
 - Event Movement Modules that raises and lowers event attraction modules, such as LED Tubes, Flashers, etc.
- **15.6" LCD driven by Network Digital Signage Player**
 - 10/100M Ethernet with RJ-45 connector
 - Storage on Compact Flash (CF) card up to 32GB
 - NTP, FTP Client, HTTP Client
 - Download Performance over 300KBps with intranet HTTP server (CF Card: Sandisk Extreme IV)
 - Playback Formats of SD Video (1366x768): MPEG-1, MPEG-2, MPEG-4, Divx up to 720p
 - Audio Formats of WAV, MP3 (32k – 320k bps)
 - Image Format of JPEG (max resolution 5120x3840)
 - Remote Control
 - Remote Control functions of Network setup for client IP, Server IP and other settings
 - Bundled Software for Windows XP/Vista to load, control and monitor client's status and activity
 - RSS feed capable
- **Includes several customizable Celebration videos**
- **Translucent bezel on sides of LCD contains 24 ultra-bright Nichia RGB LED's for a multi-colored light show**



- Pre-programmed with unique flashing patterns and different color combinations
- Backlight graphic panel available in place of LCD
- Front of video topper has ability for custom branded graphic to be inserted
- Confetti capsules are spring loaded and sprays over 20 color stripes with 6 colors and colorful effects for 3-6 feet (1-2 meters) in the air
- Body construction black UL-94 VO flame resistant plastic
- Requires +12vdc
- 3 different mounting base adapters available - Flat, Round, or Slant
- Tower light optional
- Patent Pending



Detail View of Topper Input



Detail View of Topper Connectors

Celebration Topper Part Numbers

Part Number	15.6" LCD	Media Card, Wired Network	Audio Amp. & Speakers	Confetti Launchers	Game Interface PCB, SAS	Event Module, Fiber Optic	Chrome Front Bezel	Black Front Bezel	Tower Light, Black	Tower Light, Chrome	RGB Side LED lights
RBM-754K-E1	X							X	X		X
RBM-754K-F1	X							X	X		
RBM-754S-E1	X						X			X	X
RBM-754K-A1	X	X	X					X	X		X
RBM-754S-A1	X	X	X				X			X	X
RBM-754K-C1	X	X	X	X	X			X	X		X
RBM-754S-C1	X	X	X	X	X		X			X	X



Remote Control Included



95-0124-00 Confetti Capsule Refill (Sold Separately)

TOPPER BASES



RBM-628C Flat Base with Adapter



104-0025 Flat Base



RBM628E Slant Base



RBM-628D Radius Base

SUZO-HAPP GROUP

1743 Linneman Road Mount Prospect, IL 60056
 Phone 847-593-6130 | Fax 847-593-6137
 Toll Free Phone 888-289-4277 | Las Vegas Phone 888-289-4277
 Toll Free Fax 800-593-4277 | Minnesota Phone 800-511-1796 x7214

EASY-TO-USE
 SHOPPING CART ONLINE
 24 HOURS A DAY

suzohapp.com



SAFE SIGN-UP
 FOR EMAIL
 PROMOTIONS NOT
 AVAILABLE IN OUR
 PRINT FLYERS



or sign-up at na.suzohapp.com