



FL-CA1128

Front Load Bill Validator Software Description

10 CAD (2018) Ready!

1. CURRENCY:

**5, 10, 20, 50, 100 Canadian Dollar (CAD)
(Supported Denomination Set SDS-CAD5-R2)**

2. COMMUNICATION PROTOCOL: CCNET

3. COMPATIBILITY:

(M)FL devices with:

Sense-a-Click Set	Power Interface
FLS-1801/1802	FLP-2510/2710 FLP-5710/9028

4. DIP SWITCHES SETTINGS:

SW. #1	ON State	OFF State	Default Setting
SW 1.1	Reserved	Reserved	ON
SW 1.2	Reserved	Reserved	ON
SW 1.3	5 CAD Enabled	5 CAD Disabled	ON
SW 1.4	10 CAD Enabled	10 CAD Disabled	ON
SW 1.5	20 CAD Enabled	20 CAD Disabled	ON
SW 1.6	50 CAD Enabled	50 CAD Disabled	ON
SW 1.7	100 CAD Enabled	100 CAD Disabled	ON
SW 1.8	Reserved	Reserved	ON
SW. #2	ON State	OFF State	
SW 2.1	Four Way	One Way	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

5. BILL TABLE:

BILL TYPE	DENOMINATION
0	-
1	-
2	5 CAD
3	10 CAD
4	20 CAD
5	50 CAD
6	100 CAD

6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-CAD5-R2
- CCNET Protocol Description: - Part # MAN-CCNET
- Test Software: - Part # OPT-SW-CCNET