



FL-AR2018

**Front Load Bill Validator
Software Description**

50 ARS (2018) Ready!

1. CURRENCY:

**5, 10, 20, 50, 100, 200, 500, 1000 Argentine Peso (ARS)
(Supported Denomination Set SDS-ARS8-R2)**

2. COMMUNICATION PROTOCOL:

FL Bi-Directional Protocol

3. COMPATIBILITY:

(M)FL devices with:

Sense-a-Click Set	Power Interface
FLS-1704/1706	FLP-2510/2710 FLP-5710/9028 FLP-1710/9027

4. DIP SWITCHES SETTINGS:

SW. #1	ON State	OFF State	Default Setting
SW 1.1	500 ARS Enabled	500 ARS Disabled	ON
SW 1.2	1000 ARS Enabled	1000 ARS Disabled	ON
SW 1.3	5 ARS Enabled	5 ARS Disabled	ON
SW 1.4	10 ARS Enabled	10 ARS Disabled	ON
SW 1.5	20 ARS Enabled	20 ARS Disabled	ON
SW 1.6	50 ARS Enabled	50 ARS Disabled	ON
SW 1.7	100 ARS Enabled	100 ARS Disabled	ON
SW 1.8	200 ARS Enabled	200 ARS Disabled	ON
SW. #2	ON State	OFF State	
SW 2.1	Four Way	One Way	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

5. COMMUNICATION PROTOCOL FEATURES:

- INTERRUPT MODE SUPPORTED;
- DATA SETTING SPECIFICATION

Credit Message	DENOMINATION
61h	500 ARS
62h	-
63h	5 ARS
64h	10 ARS
65h	20 ARS
66h	50 ARS
67h	100 ARS
68h	200 ARS
69h	1000 ARS

6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-ARS8-R2