



FL-IN1113

Front Load Bill Validator Software Description

New 500 INR (2016) Ready!

New 2000 INR (2016) Ready!

1. CURRENCY:

**5, 10, 20, 50, 100, 500, 2000 Indian Rupee (INR)
(Supported Denomination Set SDS-INR7-R1)**

2. COMMUNICATION PROTOCOL: CCNET

3. COMPATIBILITY:

(M)FL devices with:

Sense-a-Click Set	Power Interface
FLS-1705/1707	FLP-2510/2710 FLP-5710/9028

4. DIP SWITCHES SETTINGS:

SW. #1	ON State	OFF State	Default Setting
SW 1.1	5 INR Enabled	5 INR Disabled	ON
SW 1.2	10 INR Enabled	10 INR Disabled	ON
SW 1.3	20 INR Enabled	20 INR Disabled	ON
SW 1.4	50 INR Enabled	50 INR Disabled	ON
SW 1.5	100 INR Enabled	100 INR Disabled	ON
SW 1.6	500 INR Enabled	500 INR Disabled	ON
SW 1.7	Reserved	Reserved	ON
SW 1.8	2000 INR Enabled	2000 INR Disabled	ON
SW. #2	ON State	OFF State	
SW 2.1	Four Way	One Way	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

5. BILL TABLE:

BILL TYPE	DENOMINATION
0	-
1	-
2	5 INR
3	10 INR
4	20 INR
5	50 INR
6	100 INR
7	-
8	500 INR
9	-
10	2000 INR

6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-INR7-R1
- CCNET Protocol Description: - Part # MAN-CCNET
- Test Software: - Part # OPT-SW-CCNET