



FL-KZ1126

**Front Load Bill Validator
Software Description**

500 KZT (2017) Ready!

1. CURRENCY:

**200, 500, 1000, 2000, 5000, 10000, 20000
Kazakhstani Tenge (KZT)
(Supported Denomination Set SDS-KZT7-R4)**

2. COMMUNICATION PROTOCOL: CCNET

3. COMPATIBILITY:

(M)FL devices with:

| Sense-a-Click Set | Power Interface |
|--------------------------|--------------------------------|
| FLS-1704/1706 | FLP-2510/2710 FLP-5710/9028 |

4. DIP SWITCHES SETTINGS:

| SW. #1 | ON State | OFF State | Default Setting |
|--------|-------------------|--------------------|-----------------|
| SW 1.1 | Reserved | Reserved | ON |
| SW 1.2 | 200 KZT Enabled | 200 KZT Disabled | ON |
| SW 1.3 | 500 KZT Enabled | 500 KZT Disabled | ON |
| SW 1.4 | 1000 KZT Enabled | 1000 KZT Disabled | ON |
| SW 1.5 | 2000 KZT Enabled | 2000 KZT Disabled | ON |
| SW 1.6 | 5000 KZT Enabled | 5000 KZT Disabled | ON |
| SW 1.7 | 10000 KZT Enabled | 10000 KZT Disabled | ON |
| SW 1.8 | 20000 KZT Enabled | 20000 KZT Disabled | ON |
| SW#2 | ON State | OFF State | |
| SW 2.1 | Four Way | One Way | ON |
| SW 2.2 | High Acceptance | High Security | ON |
| SW 2.3 | 9 600 bps | 19 200 bps | ON |
| SW 2.4 | Service | Host Machine | OFF |

5. BILL TABLE:

| BILL TYPE | DENOMINATION |
|-----------|--------------|
| 0 | - |
| 1 | 200 KZT |
| 2 | 500 KZT |
| 3 | 1000 KZT |
| 4 | 2000 KZT |
| 5 | 5000 KZT |
| 6 | 10000 KZT |
| 7 | 20000 KZT |

6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-KZT7-R4
- CCNET Protocol Description: - Part # MAN-CCNET
- Test Software: - Part # OPT-SW-CCNET