



FL-ZA1120

Front Load Bill Validator Software Description

New ZAR (2018) Ready!

1. CURRENCY:

**10, 20, 50, 100, 200 South African Rand (ZAR)
(Supported Denomination Set SDS-ZAR5-R2)**

2. COMMUNICATION PROTOCOL: CCNET

3. COMPATIBILITY:

(M)FL devices with:

Sense-a-Click Set	Power Interface
FLS-1704/1706	FLP-2510/2710 FLP-5710/9028

4. DIP SWITCHES SETTINGS*:

SW. #1	ON State	OFF State	Default Setting
SW 1.1	10 ZAR Enabled	10 ZAR Disabled	ON
SW 1.2	20 ZAR Enabled	20 ZAR Disabled	ON
SW 1.3	50 ZAR Enabled	50 ZAR Disabled	ON
SW 1.4	100 ZAR Enabled	100 ZAR Disabled	ON
SW 1.5	200 ZAR Enabled	200 ZAR Disabled	ON
SW 1.6	Old ZAR Enabled	Old ZAR Disabled	ON
SW 1.7	Reserved	Reserved	ON
SW 1.8	Reserved	Reserved	ON
SW. #2	ON State	OFF State	
SW 2.1	Four Way	One Way	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

*- Detection and rejection of stain notes are activated in High Security mode.

5. BILL TABLE:

BILL TYPE	DENOMINATION
0	10 ZAR
1	20 ZAR
2	50 ZAR
3	100 ZAR
4	200 ZAR

6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-ZAR5-R2
- CCNET Protocol Description: - Part # MAN-CCNET
- Test Software: - Part # OPT-SW-CCNET