



FL-ZALS2015

Front Load Bill Validator

Software Description

ZAR (2018) Ready!

1. CURRENCY:

10, 20, 50, 100, 200 South African Rand (ZAR)

10, 20, 50, 100, 200 Lesotho Loti (LSL)

(Supported Denomination Set SDS-ZAR5LSL5-R1)

2. COMMUNICATION PROTOCOL:

FL Bi-Directional Protocol

3. COMPATIBILITY:

(M)FL devices with:

Sense-a-Click Set	Power Interface
FLS-1704/1706	FLP-2510/2710 FLP-5710/9028 FLP-1710/9027

4. DIP SWITCHES SETTINGS:

SW. #1	ON State	OFF State	Default Setting
SW 1.1	10 ZAR/LSL Enabled	10 ZAR/LSL Disabled	ON
SW 1.2	20 ZAR/LSL Enabled	20 ZAR/LSL Disabled	ON
SW 1.3	50 ZAR/LSL Enabled	50 ZAR/LSL Disabled	ON
SW 1.4	100 ZAR/LSL Enabled	100 ZAR/LSL Disabled	ON
SW 1.5	200 ZAR/LSL Enabled	200 ZAR/LSL Disabled	ON
SW 1.6	Old ZAR Enabled	Old ZAR Disabled	ON
SW 1.7	Reserved	Reserved	ON
SW 1.8	ZAR Enabled	ZAR Disabled	ON
SW. #2	ON State	OFF State	
SW 2.1	Reserved	Reserved	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

*- Detection and rejection of stain notes are activated in High Security mode.

5. COMMUNICATION PROTOCOL FEATURES:

- INTERRUPT MODE SUPPORTED;
- DATA SETTING SPECIFICATION:

Credit Message	Denomination
61h	-
62h	-
63h	-
64h	10 ZAR/LSL
65h	20 ZAR/LSL
66h	50 ZAR/LSL
67h	100 ZAR/LSL
68h	200 ZAR/LSL

Program CRC (Seed = 0) - 561B

6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-ZAR5LSL5-R1