



# FL-ZASZ1115

Front Load Bill Validator

Software Description

**ZAR (2018) Ready!**

**100 SZL (2018) Ready!**

**200 SZL (2018) Ready!**

## 1. CURRENCY:

**10, 20, 50, 100, 200 South African Rand (ZAR)**  
**10, 20, 50, 100, 200 Swazi Lilangeni (SZL)**  
**(Supported Denomination Set SDS-ZAR5SZL5-R1)**

## 2. COMMUNICATION PROTOCOL: CCNET

## 3. COMPATIBILITY:

**(M)FL devices with:**

Sense-a-Click Set	Power Interface
FLS-1704/1706	FLP-2510/2710 FLP-5710/9028

**4. DIP SWITCHES SETTINGS\*:**

<b>SW. #1</b>	<b>ON State</b>	<b>OFF State</b>	<b>Default Setting</b>
SW 1.1	10 ZAR/SZL Enabled	10 ZAR/SZL Disabled	ON
SW 1.2	20 ZAR/SZL Enabled	20 ZAR/SZL Disabled	ON
SW 1.3	50 ZAR/SZL Enabled	50 ZAR/SZL Disabled	ON
SW 1.4	100 ZAR/SZL Enabled	100 ZAR/SZL Disabled	ON
SW 1.5	200 ZAR/SZL Enabled	200 ZAR/SZL Disabled	ON
SW 1.6	Old ZAR Enabled	Old ZAR Disabled	ON
SW 1.7	Reserved	Reserved	ON
SW 1.8	All ZAR Enabled	All ZAR Disabled	ON
<b>SW. #2</b>	<b>ON State</b>	<b>OFF State</b>	
SW 2.1	Four Way	One Way	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

\* - Detection and rejection of stain notes are activated in High Security mode

**5. BILL TABLE:**

<b>BILL TYPE</b>	<b>DENOMINATION</b>
0	10 ZAR/SZL
1	20 ZAR/SZL
2	50 ZAR/SZL
3	100 ZAR/SZL
4	200 ZAR/SZL

**6. OPTIONAL ACCESSORIES AND DOCUMENTS:**

- Supported Denomination Set: - Part # SDS-ZAR5SZL5-R1
- Protocol Description: - Part # MAN-CCNET
- Test Software: - Part # OPT-SW-CCNET