



# FL-ZM1112

## Front Load Bill Validator Software Description

### 1. CURRENCY:

**2, 5, 10, 20, 50, 100** **Zambian Kwacha (ZMW)**  
**(Supported Denomination Set SDS-ZMW6-R1)**

### 2. COMMUNICATION PROTOCOL: **CCNET**

### 3. COMPATIBILITY:

**(M)FL devices with:**

<b>Sense-a-Click Set</b>	<b>Power Interface</b>
FLS-1704/1706	FLP-2510/2710 FLP-5710/9028

#### 4. DIP SWITCHES SETTINGS:

SW. #1	ON State	OFF State	Default Setting
SW 1.1	Reserved	Reserved	ON
SW 1.2	2 ZMW Enabled	2 ZMW Disabled	ON
SW 1.3	5 ZMW Enabled	5 ZMW Disabled	ON
SW 1.4	10 ZMW Enabled	10 ZMW Disabled	ON
SW 1.5	20 ZMW Enabled	20 ZMW Disabled	ON
SW 1.6	50 ZMW Enabled	50 ZMW Disabled	ON
SW 1.7	100 ZMW Enabled	100 ZMW Disabled	ON
SW 1.8	Reserved	Reserved	ON
<b>SW#2</b>	<b>ON State</b>	<b>OFF State</b>	
SW 2.1	Four Way	One Way	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

#### 5. BILL TABLE:

BILL TYPE	DENOMINATION
0	-
1	2 ZMW
2	5 ZMW
3	10 ZMW
4	20 ZMW
5	50 ZMW
6	100 ZMW

#### 6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-ZMW6-R1
- CCNET Protocol Description: - Part # MAN-CCNET
- Test Software: - Part # OPT-SW-CCNET