



FL-ZM2015

Front Load Bill Validator

Software Description

1. CURRENCY:

**2, 5, 10, 20, 50, 100 Zambian Kwacha (ZMW)
(Supported Denomination Set SDS-ZMW6-R1)**

2. COMMUNICATION PROTOCOL:

FL Bi-Directional Protocol

3. COMPATIBILITY:

(M)FL devices with:

Sense-a-Click Set	Power Interface
FLS-1704/1706	FLP-2510/2710 FLP-5710/9028 FLP-1710/9027

4. DIP SWITCHES SETTINGS:

SW. #1	ON State	OFF State	Default Setting
SW 1.1	Reserved	Reserved	ON
SW 1.2	2 ZMW Enabled	2 ZMW Disabled	ON
SW 1.3	5 ZMW Enabled	5 ZMW Disabled	ON
SW 1.4	10 ZMW Enabled	10 ZMW Disabled	ON
SW 1.5	20 ZMW Enabled	20 ZMW Disabled	ON
SW 1.6	50 ZMW Enabled	50 ZMW Disabled	ON
SW 1.7	100 ZMW Enabled	100 ZMW Disabled	ON
SW 1.8	Reserved	Reserved	ON
SW#2	ON State	OFF State	
SW 2.1	Four Way	One Way	ON
SW 2.2	High Acceptance	High Security	ON
SW 2.3	9 600 bps	19 200 bps	ON
SW 2.4	Service	Host Machine	OFF

5. COMMUNICATION PROTOCOL FEATURES:

- INTERRUPT MODE SUPPORTED;
- DATA SETTING SPECIFICATION:

Credit Message	Denomination
61h	-
62h	2 ZMW
63h	5 ZMW
64h	10 ZMW
65h	20 ZMW
66h	50 ZMW
67h	100 ZMW

6. OPTIONAL ACCESSORIES AND DOCUMENTS:

- Supported Denomination Set: - Part # SDS-ZMW6-R1